

## BX-23 Series Outdoor Bell Box

High Quality Bell Box with Effective Visual and Audible Alerts



- Four selectable siren volume levels
- Industry-Leading RF Technology
- IP56 Waterproof and Dustproof Housing
- Battery Operated or AC Powered

BX-23 series Bell Box is a wireless, bi-directional outdoor sounder generating loud 107-decibel siren sounds and strobe lights during an alarm to provide visible and audible alerts. The bell box can either be powered by an AC adaptor or battery-operated.

BX-23-F1 integrates Climax industry-leading F1 RF technology to deliver accelerated signal transmission and record-breaking communication. The astonishing capability to communicate with the control panel across vast expanses provides increased installation flexibility, especially on large or complicated premises, making BX-23-F1 not only suitable for residential premises but commercial premises as well.

BX-23 series also provides tamper-deterrent feature to protect against unauthorized removal or sabotage. Encased in sleek, IP56-rated water and dust resistant housing, BX-23 series blends naturally with any building's exterior. BX-23 series' immediate warning signals help speed up the response time during an emergency, making it an essential component of any security system requiring effective alarm alerts.

### Features

- Siren output level is 107dB at 1 meter
- F1 RF technology accelerate the speed of signal transmission, boosts communication range
- Four programmable siren duration options
- Four selectable siren volume levels
- Programmable strobe activation
- Unique alarm sounds for fire and burglary
- Battery-operated or AC-powered
- Compliant with CE requirement
- IP56 waterproof and dustproof housing
- Beep notification of arming/disarming, door chime and low battery status
- Regular supervision signals to check system integrity and trouble shooting
- Tamper protection prevents unauthorized removal or sabotage
- Low battery detection
- Compliant with EN50131-4 / EN50131-5-3 Grade II, Class IV

## BX-23 Series Outdoor Bell Box

### Specifications

#### BX-23-F1

Frequency	868 MHz / 433 MHz
Power Source	1.5V, D Alkaline batteries x 4
Optional Power Source	9V, 1A AC Adaptor
Battery Life	4.1 years*
Siren Output	107dB at 1 meter
Strobe Light Cover	Blue (other colors available upon request)
Operating Temperature	-25°C to 60°C (-13°F to 140°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	205mm x 83mm x 317mm

\* Note: Actual battery life may vary with product settings, usage patterns and operating environment.

#### BX-23

Frequency	868 MHz / 433 MHz
Power Source	1.5V, D Alkaline batteries x 4
Optional Power Source	9V, 1A AC Adaptor
Battery Life	4.9 years*
Siren Output	107dB at 1 meter
Strobe Light Cover	Blue (other colors available upon request)
Operating Temperature	-25°C to 60°C (-13°F to 140°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	205mm x 83mm x 317mm

\* Note: The actual battery life may vary with product settings, usage patterns and operating environment.

### Ordering Information

**BX-23-F1** Outdoor Bell Box with extensive RF range, compatible only with Climax F1 Control Panels

**BX-23** Outdoor Bell Box, compatible with all Climax Control Panels

Distribuito da:

**KREGA**  
DISTRIBUZIONE  
Innovazioni Elettroniche e Meccaniche